



# LUMINI LED RETROFIT

Project Name: \_\_\_\_\_ Model Number: \_\_\_\_\_  
 Prepared By: \_\_\_\_\_ Date: \_\_\_\_\_

## LED RETROFIT ADAPTORS

Available bases for DCB, Intermediate, and Medium. For 120VAC or UDC applications. Less than 2 watts.

## OPERATION

Universal emergency circuit (UDC): 6VDC to 24VDC. 120VAC or 347VAC Input (347V is for hard wired version only).

## MODEL OPTIONS

- LUMINI-I** for an Intermediate based **LUMINI** 120VAC.
- LUMINI-M** for a Medium based **LUMINI** 120VAC.
- LUMINI-D** for a DC Bayonet based **LUMINI** 120VAC.
- LUMINI-HW** for a Hard Wired 120VAC or 347VAC **LUMINI**.

## DIMENSIONS

- Exit 11 3/8" (length) x 1" (width) x 78" (height)
- Sortie 16 3/8" (length) x 1" (width) x 78" (height)
- B6L 26 3/8" (length) x 1" (width) x 78" (height)

1 year warranty

## ORDERING GUIDE

SERIES	BASE	SIZE	COLOUR	OPERATION
LUMINI	I (Intermediate)	Blank (Exit)	Blank (Red)	UDC (Universal 6-24VDC)
	M (Medium)	SORTIE (Sortie)	G (Green)	120V (120VAC input)
	D (DC Bayonet)	B6L (Bilingual)	W (White)	

SERIES	BASE	SIZE	COLOUR	OPERATION
LUMINI	HW (Hard Wired)	EXIT	Blank (Red)	UDC (Universal 6-24VDC)
		SORTIE	G (Green)	120V (120VAC input)
		B6L	W (White)	*347V (347VAC input)

NOTE: \*347V is available in Hard Wired base only



# REDLED LAMPS

Project Name: \_\_\_\_\_

Model Number: \_\_\_\_\_

Prepared By: \_\_\_\_\_

Date: \_\_\_\_\_

## ULTRA BRIGHT LED LAMP RETROFIT DEVICE

Interchangeable bases included: Candelabra, DCB and Intermediate. Optional medium base available (please specify). Ultra bright light output. For 120VAC applications. 1.4 watts per lamp. 1 year warranty. Two lamps per kit

## DIMENSIONS

Each lamp is 5 1/8" tall and 1 5/8" wide.  
(add 1/8" when using adapters)

## HOW TO ORDER

### REDLED-U-KIT

**REDLED-U-KIT-M** (for two [2] 120VAC LED lamps c/w interchangeable Candelabra base, DCB base and Intermediate base) and medium base. Product is always shipped in quantities of two [2] lamps per package. The above are screw in style retrofit lamps suitable for 120VAC exit and sortie sign applications.